

Low Voltage Detector with Flashlight



LVD-26

The non-contact Voltage Detector is intended to check for the presence of AC Voltage, signaling the user with an audible alarm (intermittent tone) and a flashing LED.

It's used to detect voltage in outlets, lighting fixtures, circuit breakers, wires, and cables or to find a break in a wire.

FEATURES

- Bright LED and audible alarm sound when voltage is present.
- Designed for non-contact voltage detection.
- Can be used to find a break in a wire.
- Flashlight function.
- ON/OFF switch for longer battery life.

SPECIFICATIONS

Voltage detection	50V~1000V AC
Frequency	50~500 Hz
Measurement category	CAT III 1000V
Indication	Audible alarm (intermittent tone) and LED
Operating conditions	Temperature : 0~40°C Humidity : Less than 80% R.H. Altitude : 2000m maximum
Power source	1.5V (AAA) × 2
Dimension	167 (L) × 27 (W) × 29.5 (D) mm
Weight (batteries included)	Approx. 54g
Safety standard	EN 61010-1 EN 61326-1 IEC 61000-4-2 IEC 61000-4-3 IEC 61000-4-8

